## **Bespoke Honey Warming Kit Instructions**

This 25W element kit is designed for a cabinet approximately 700x400x550mm high.

- Before fitting ensure the element is not connected to the mains supply.
- To mount the element position the screw eyes in each corner approximately 100mm above the floor of the cabinet.
- Suspend the element from the screw eyes using the silicone ties provided. DO NOT LAY
  ON SHELF ELEMENT MUST BE SUSPENDED.
- The capillary thermostat must be mounted inside the cabinet, ideally behind the control box using the heat resistant tape. For ease of use we would recommend the black element cable enters the cabinet at the base.
- It is not essential that the control box is mounted on the cabinet. If it is used remotely be aware of the limitations of the capillary thermostat.
- Caution should be taken to ensure the element does not come in contact with liquids or the mains cable (fitted with a 3 amp fuse)

On an insulated cabinet such as our normal stock item you can expect the following temperatures to be attained.

- 20°C 2 minutes
- 30°C 4 minutes
- 40°C 8 minutes
- 50°C 16 minutes
- 70°C 54 minutes

Maximum attainable temperature is approximately 90°C

DO NOT LEAVE THE LID OF THE WARMING CABINET OPEN FOR MORE THAN 5 MINUTES WHEN THE THERMOSTAT IS ON

## Wiring Instructions

- 1. Remove the four screws from the enclosure
- 2. Feed the cable into the box using the vacant gland at the bottom
- 3. The brown wire of the white power cable is marked 11, This is connected onto terminal 11 on the thermostat.
- 4. The blue wire of the power cable is connected to the blue wire of the heater by the male/female connectors
- 5. The brown wire of the heater is marked 12, this is connected to terminal 12 on the thermostat.
- 6. The earth wire (green/yellow) is connected to the silver terminal to the left of number 11 on the thermostat.
  - 7. The off position is when the arrow on the dial is opposite the red dot on the enclosure.

If in doubt, consult a qualified electrician.

